

# Gen Set Power Selector Chart

EU2007 97/68/EC Certified Models

2009 Issue 1

**50Hz**

Model	EU Emissions Level	Net Engine Output			Typical Generator Efficiency %	Typical Power Factor	Typical Generating Set Output						1500/1800 rev/min switchable
		Baseload kWm	Prime kWm	Standby kWm			Baseload		Prime		Standby		
							kWe	kVA	kWe	kVA	kWe	kVA	

## 3000 rev/min (17.5 kVA to 37.2 kVA)

<b>403D-11G</b>	Stage 2	*	16.1	17.9	86	0.8	*	*	14.0	17.5	15.6	19.5	
<b>403D-15G</b>	Stage 2	*	20.7	22.9	87	0.8	*	*	18.0	22.5	19.9	24.9	
<b>404D-22G</b>	Stage 2	*	30.2	33.4	89	0.8	*	*	26.9	33.6	29.7	37.2	

## 1500 rev/min (20 kVA to 650 kVA)

<b>404D-22G</b>	Stage 2	*	18.4	20.3	88	0.8	*	*	16.0	20.0	17.7	22.1	
<b>404D-22TG</b>	Stage 2	*	24.9	27.4	88	0.8	*	*	21.9	27.4	24.1	30.1	■
<b>1103C-33G2</b>	Stage 2	*	27.3	30.4	90	0.8	*	*	24.6	30.7	27.4	34.2	■
<b>1103C-33G3</b>	Stage 2	*	27.3	30.4	90	0.8	*	*	24.6	30.7	27.4	34.2	
<b>1103C-33TG2</b>	Stage 2	*	40.9	45.6	90	0.8	*	*	36.8	46.0	41.0	51.3	■
<b>1103C-33TG3</b>	Stage 2	*	40.9	45.6	90	0.8	*	*	36.8	46.0	41.0	51.3	
<b>1104C-44TG2</b>	Stage 2	*	53.7	59.3	90	0.8	*	*	48.3	60.4	53.4	66.7	■
<b>1104C-44TG3</b>	Stage 2	*	53.7	59.3	90	0.8	*	*	48.3	60.4	53.4	66.7	■
<b>1104C-44TAG1</b>	Stage 2	*	71.5	79.0	90	0.8	*	*	64.4	80.4	71.1	88.8	■
<b>1104C-44TAG2</b>	Stage 2	*	90.1	99.5	90	0.8	*	*	81.4	101.4	89.6	111.9	■
<b>1106C-E66TAG2</b>	Stage 2	*	119.5	133.0	92	0.8	*	*	109.9	137.4	122.4	152.9	■
<b>1106C-E66TAG3</b>	Stage 2	*	129.0	143.5	93	0.8	*	*	120.0	150.0	133.4	166.8	■
<b>1106C-E66TAG4</b>	Stage 2	*	158.4	175.5	93	0.8	*	*	147.3	184.1	163.2	204.0	■
<b>1306C-E87TAG3</b>	Stage 2	164	180	199	92	0.8	151	189	166	208	183	229	■
<b>1306C-E87TAG4</b>	Stage 2	179	198	217	92	0.8	165	205	182	228	200	250	■
<b>1306C-E87TAG5</b>	Stage 2	185	204	224	92	0.8	170	213	188	235	206	258	
<b>1306C-E87TAG6</b>	Stage 2	198	218	239	92	0.8	182	228	200	250	220	275	
<b>2206C-E13TAG2</b>	Stage 2	*	305	349	93	0.8	*	*	280	350	320	400	■
<b>2206C-E13TAG3</b>	Stage 2	*	349	392	93	0.8	*	*	320	400	360	450	■
<b>2506C-E15TAG1</b>	Stage 2	*	396	435	92	0.8	*	*	364	455	400	500	■
<b>2506C-E15TAG2</b>	Stage 2	*	435	478	92	0.8	*	*	400	500	440	550	■
<b>2806C-E18TAG1A</b>	Stage 2	*	514	565	92	0.8	*	*	473	591	520	650	■

\*Available on application

■ Switchable engines must be requested at point of order, please consult with your local Perkins representative.

### Notes:

- All ratings are for guidance only, please refer to the specific engine technical data sheet for final powers.
- Perkins conditions of sale apply.
- Electrical output is based on typical generator efficiency and is for guidance only.
- All ratings data based on operation under ISO 8528-1, ISO 3046, DIN6271 conditions using typical fan sizes and drive ratios. Performance tolerance quoted by Perkins is ± 5%.
- **Baseload Power** = Power available for continuous full load operation. An overload of 10% permitted for one hour in every twelve hours of operation.
- **Prime Power** = Power available at variable load in lieu of main power network (please refer to the engine Technical Data Sheets for engine load factors). An overload of 10% permitted for one hour in every twelve hours of operation.
- **Standby Power** = Power available at a variable load in the event of a main power network failure up to a maximum of 500 hours per year. No overload is permitted.

# Gen Set Power Selector Chart

EPA 40 CFR Part 89 Certified Models

**60Hz**

Model	EPA Emissions Level	Net Engine Output			Typical Generator Efficiency %	Typical Power Factor	Typical Generating Set Output						1500/1800 rev/min switchable
		Baseload kWm	Prime kWm	Standby kWm			Baseload		Prime		Standby		
							kWe	kVA	kWe	kVA	kWe	kVA	

## 1800 rev/min (9 kWe to 600 kWe)

<b>403D-11G</b>	Tier 4	*	10.3	11.4	87	0.8	*	*	9.0	11.2	9.9	12.4	
<b>403D-15G</b>	Tier 4	*	14.4	15.9	88	0.8	*	*	12.7	15.8	14.0	17.5	■
<b>404D-22G</b>	Interim Tier 4	*	21.6	23.9	89	0.8	*	*	19.2	24.0	21.3	26.6	■
<b>404D-22TG</b>	Interim Tier 4	*	29.6	32.6	89	0.8	*	*	26.3	32.9	29.0	36.3	■
<b>404D-22TAG</b>	Interim Tier 4	*	32.4	35.7	90	0.8	*	*	29.2	36.5	32.1	40.2	
<b>1104D-44TG1</b>	Tier 3	*	57.0	63.0	90	0.8	*	*	51.3	64.1	56.7	70.9	
<b>1104D-E44TG1</b>	Tier 3	*	65.2	71.8	90	0.8	*	*	58.7	73.4	64.6	80.8	
<b>1104D-E44TAG1</b>	Tier 3	*	82.0	90.8	90	0.8	*	*	73.8	92.0	81.7	102.0	
<b>1104D-E44TAG2</b>	Tier 3	*	100.0	111.0	90	0.8	*	*	90.0	113.0	100.0	125.0	
<b>1106D-E66TAG2</b>	Tier 3	*	136.6	153.6	92	0.8	*	*	125.0	156.0	140.0	175.0	
<b>1106D-E66TAG3</b>	Tier 3	*	142.4	159.4	92	0.8	*	*	135.0	169.0	150.0	188.0	
<b>1106D-E66TAG4</b>	Tier 3	*	173.7	192.3	92	0.8	*	*	156.0	200.0	175.0	219.0	
<b>2206D-E13TAG2</b>	Tier 3	*	349	381	93	0.8	*	*	320	400	350	438	
<b>2206D-E13TAG3</b>	Tier 3	*	381	435	93	0.8	*	*	350	438	400	500	
<b>2506D-E15TAG1</b>	Tier 3	*	435	490	92	0.8	*	*	400	500	450	563	
<b>2506C-E15TAG3</b>	Tier 2	*	495	543	92	0.8	*	*	455	569	500	625	
<b>2506C-E15TAG4#</b>	Tier 2	-	-	597	92	0.8	-	-	-	-	550	687	
<b>2806C-E18TAG3</b>	Tier 2	*	592	652	92	0.8	*	*	545	681	600	750	■

\*Available on application # Emergency Standby Power only

■ Switchable engines must be requested at point of order, please consult with your local Perkins representative.

### Notes:

- All ratings are for guidance only, please refer to the specific engine technical data sheet for final powers.
- Perkins conditions of sale apply.
- Electrical output is based on typical generator efficiency and is for guidance only.
- All ratings data based on operation under ISO 8528-1, ISO 3046, DIN6271 conditions using typical fan sizes and drive ratios. Performance tolerance quoted by Perkins is ± 5%.
- **Baseload Power** = Power available for continuous full load operation. An overload of 10% permitted for one hour in every twelve hours of operation.
- **Prime Power** = Power available at variable load in lieu of main power network (Please refer to the engine Technical Data Sheets for engine load factors). An overload of 10% permitted for one hour in every twelve hours of operation.
- **Standby Power** = Power available at a variable load in the event of a main power network failure up to a maximum of 500 hours per year. No overload is permitted.
- **Emergency Standby Power** = Power available in the event of a main power network failure, up to maximum of 200 hours per year which may be run continuously. Load factor may be up to 70% of the Emergency Standby Power rating. No overload is permitted.



### Perkins Engines Company Limited

Peterborough PE1 5NA United Kingdom

Tel: +44 (0)1733 583000

Fax: +44 (0)1733 582240

www.perkins.com